

Wachendorff Automation GmbH & Co. KG

Industriestraße 7 • D-65366 Geisenheim

Tel.: +49 (0) 67 22/99 65-25 • Fax: +49 (0) 67 22/99 65-70

E-Mail: wdg@wachendorff.de • www.wachendorff-automation.com

Installation Kit for frequency-control lifts WDGAS58E with end hollow shaft encoder



The following installation kits are available for fitting the encoder to a frequency controlled lift. Every installation kit consists:

1 x Encoder, 1 x with 15 m ready-made shielded cable, 1 x shaft adapter

Mechanical Data

Housing

- Flange: Aluminium

- Cap: Aluminium, powder coated

- Torque Support:

Incl. 1 spring plate WDGDS10001 1. Spring plate

Compensation: axial: ±0.8 mm

radial: ±0.2 mm

Max. operating 6000 rpm

speed:

Hollow bore (blind)

- Material: stainless steel

- Diameter: 10

- Permitted load max. 80 N radial on shaft end: max. 60 N axial

- Starting torque: approx. 1.6 Ncm at ambient temperature permanently attached clambing ring Attachment:

Bearings

Type: 2 precision ball bearings

Service life: 1x 10° revs. at 100 % shaft load

1x 10¹⁰ revs. at 40 % shaft load 1x 1011 revs. at 20 % shaft load

Weight: approx. 220 g

Connections: SH8: radial connector, 8 pin

Protection rating: **IP65**

(EN 60529)

Operating temperature: -20 °C up to +80 °C -30 °C up to +80 °C Storage temperature:

Machinery Directive: basic data safety integrity level

MTTF_d: 200 a Mission time (T,,): 25 a

1x 1011 revs. at 6000 rpm and Nominale service life 20 % rated shaft load

Diagnostic coverage (DC): 0 %

WDGI58E-YYYY-ABN-H24-SH8 Encoder-Order No.:

- YYYY: with 1024, 2048, 4096 PPR

- 3 channels, A, B and zero marker pulse N

- H24: 10 VDC up to 30 VDC HTL Power supply

- SH8: radial connector, 8 pin

WDGI58E-YYYY-ABN-R05-SH8

- YYYY: with 1024, 2048, 4096 PPR

- 6 channels, A, B, zero marker pulse N + Inv.


- 5 VDC TTL Power supply with inv. output

- SH8: radial connector, 8 pin


YYYY: Please specify required. PPR: 1024, 2048 oder 4096

- Easy installation on all motor shafts
- Flexible attachment possibilities
- Space-saving
- TTL, HTL output
- Threads: M8, M10, M12, M16 und M20

www.wachendorff-automation.com/wdgas58e



The cable is 15m in length and is shielded, however the shield is not connected to the connector housing. With a mated connector, the encoder meets protection class IP40.



The cable has a connection as follows:

Function Colour Positive brown white Negative green A inv. red В vellow B inv. black Ν gray N inv. violet Shield: cable braiding KD84015 Order No.:

Pin identification SH8

| Function | Pin HTL | PIN TT |
|----------|---------|--------|
| Positive | 2 | 2 |
| Negative | 1 | 1 |
| Α | 3 | 3 |
| A inv. | - | 6 |
| В | 4 | 4 |
| B inv. | - | 7 |
| N | 5 | 5 |
| N inv. | - | 8 |



The view of the soldered side of the connector connector corresponds to the view of the pin arrangement on the encoder.




Shaft adapters




Shaft adapters:

The shaft adapters are screwed into an appropriate thread on the lift.



Shaft adapter M8




Order No.: WDGWA10M08

Order No.: WDGWA10M10


Order No.: WDGWA10M16

Order No.: WDGWA10M20


Shaft adapter M10



Shaft adapter M12



Shaft adapter M16



Shaft adapter M20

Note:

XX: Please insert the code corresponding to the required shaft adapter:

Shaft adapter 10/M8: 08
Shaft adapter 10/M10: 10
Shaft adapter 10/M12: 12
Shaft adapter 10/M16: 16
Shaft adapter 10/M20: 20

YYYY: Please specify required PPR: 1024, 2048 or 4096

Ordering information WDGAS58E:

| Description: | Order No.: |
|---|-------------------|
| Installation Kit 10-30 VDC HTL comprising: - WDGI58E-10-YYYY-ABN-H24-SH8 - YYYY: with 1024, 2048, 4096 PPR - 3 channels, A, B, N - H24: 10 - 30 VDC power supply - SH8: radial connector, 8 pin - KD84015: 15 m ready-made shielded cable - XX: Shaft adapter: 08, 10, 12, 16 or 20 | WDGAS58EYYYYH24XX |
| Installation Kit 5 VDC TTL, RS422 comprising: - WDGI58E-10-YYYY-ABN-R05-SH8 - YYYY: with 1024, 2048, 4096 PPR - 6 channels, A, B, N, A, B, N - R05: 5 VDC TTL power supply with inv. output circuit - SH8: radial connector, 8 pin - KD84015: 15 m ready-made shielded cable - XX: Shaft adapter: 08, 10, 12, 16 or 20 | WDGAS58EYYYYR05XX |